

ENERGETICHESKAYA



*Ioaquín Turina, nº1, 1ºa
28220 Majadahonda - Madrid
Tel. +34-916799034 mov+34 636680058*



*Energeticheskaya 13, 229
111024 Moscow - Russian
Tel. +74953613910 mov +79154884468*

6Kw y 8 Kw power inverter

Protection Features

- Overload shutdown
- Over temperature shutdown
- Low voltage alarm
- Low voltage shutdown
- High battery voltage shutdown
- Short circuit protection
- Polarity reverse connection protection

Max. Continuous Power 6000 watts

Peak Power 12000 watts

AC output voltage 110V or 120V or 220V or 230V or 240V AC

AC output frequency 50 or 60 +/-2 Hz

AC output waveform Modified Sine Wave

DC input voltage 12V or 24V or 48V or 110V DC

voltage range 10.5~15.0V or 21.0~30.0V or 42.0~60VDC

No Load Current Draw <1.8 amps(at 12V input)

LED Indicator Input voltage level, output load level and status

Efficiency (Typ.) >85%

Fuse (12V) 40A *16 (12V) / 20A *16(24V) / 10A *16(48V)

Bat. Low Alarm 10.5V or 21.0V or 42.0V DC

Bat. Low Shutdown 10.0V or 20.0V or 40.0V DC

Over Load Shut off output voltage, re-power on to recover

Over Voltag 15.5V or 31.0V or 62.0V DC

Cooling Loading controlled cooling fan

General Specifications

Dimensions 438×265×159mm(L×W×H)

Weight 11.6 kgs

